

# DCN-CONCS Concentus Channel Selector

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Low susceptibility to mobile phones
- ▶ Compact, attractive delegate unit
- ▶ Built-in, fold-away, flat-panel loudspeaker
- ▶ Five voting buttons
- ▶ Cable connections located underneath the unit

The DCN-CONCS is similar to the DCN-CON Standard Delegate Unit, but includes a built-in language channel selector. This makes it suitable for conferences where more than one language is used and simultaneous interpretations are available. The channel selector includes up and down select keys and a 2-digit display with backlighting, enabling rapid selection of the required language channel. Channel selection is automatically limited to the number of language channels available. The flat-panel loudspeaker offers superior acoustics with minimal feedback, thus increasing intelligibility. When the unit is not being used, the loudspeaker panel conveniently folds down.

## Functions

### Controls and Indicators

- Channel selector with channel number display with back lighting and channel select keys (up/down)
- Headphone volume control on each side of the unit
- Built-in fold-away flat-panel loudspeaker, automatically muted if a microphone is on
- Microphone 'on/off' or 'request-to-speak' button
- 'Microphone-on' indicator at the top of the loudspeaker
- Tri-color indicator above the microphone button:
  - Red microphone on indicator

- Green 'Request-to-speak' confirmation indicator
- Yellow 'VIP' indicator. 'VIP' is lit when the delegate unit is part of the notebook, which is only available when PC control software is used
- Five voting buttons with yellow LED confirmation indicators These can be used to register:
  - PRESENT, YES (+), NO (-), ABSTAIN (X), (parliamentary voting)
  - Numerals: 1 to 5 (multiple choice or opinion polls)
  - Rating scale: - -, -, 0, +, ++ (audience response)

### Interconnections

- Socket for pluggable microphone
- 2 m (78.7 in) cable terminated in a molded six-pole circular connector
- Socket for external microphone or headset microphone
- Six-pole circular connector for loop-through connections
- Eight-pole modular jack connector for Intercom Handset LBB 3555/00 and external present and fraud contact e.g. a fingerprint reader
- Left and right 3.5 mm (0.14 in) stereo jack type headphones sockets
- Connection 3.5 mm (0.14 in) for external microphone or stereo jack type headset microphone

**Certifications and approvals**

Region	Certification
Europe	CE

**Technical specifications****Electrical**

Headphone connection	
Frequency response	30 Hz to 20 kHz
Load impedance	> 32 ohm
Output power	2 x 15 mW/32 ohm
Headset connection	
Frequency response	30 Hz - 20 kHz
Load impedance	> 32 ohm
Output power	2 x 15 mW/32 ohm
Nominal microphone input level	7 mVrms
Overload microphone input level	> 124 mVrms
Interface data	
Recommended external microphone type (or headset microphone)	
Element	Electret-condenser
Polar pattern	Omni directional
Operating voltage	5 VDC
Sensitivity	62 dB at 1200 ohm (0 dB = 1 V/mbar at 1 kHz)
Frequency response	100 Hz to 14 kHz
Connector	3.5 mm (0.14 in) jack mono or stereo

**Mechanical**

Mounting	Tabletop (portable or fixed mounting) and flush mounting
Dimensions (H x W x D)	<b>(without microphone)</b>
Tabletop	50 x 275 x 155 mm 2.0 x 10.8 x 6.1 in)
Flush mounted	30 x 275 x 155 mm (1.2 x 10.8 x 6.1 in)
Weight	1.4 kg (3.1 lb)

Color top	Charcoal (PH 10736) with silver (RAL 9022) panel
Color base	Charcoal (PH 10736)

**Ordering information****DCN-CONCS Concentus Channel Selector**

pluggable microphone, voting, channel select, 2 headphone sockets, microphone to be ordered separately

Order number **DCN-CONCS**

**DCN-MICS Pluggable Short Microphone**

length 310 mm (12.2 inch), silver

Order number **DCN-MICS**

**DCN-MICL Pluggable Long Microphone**

length 480 mm (18.9 inch), silver

Order number **DCN-MICL**

**Represented by:**

**Americas:**

Bosch Security Systems, Inc.  
12000 Portland Avenue South  
Burnsville MN 55337, USA  
Phone: +1-800-392-3497  
Fax: +1-800-955-6831  
audiosupport@us.bosch.com  
www.boschsecurity.com

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security  
Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
al.securitysystems@bosch.com  
www.boschsecurity.com